

Q SPOT 40 TUNABLE WHITE

DMX CONTROL TABLE



1-CHANNEL-MODE					
Preselect Colour Temperature (Mode Static) , Dimmer Response and Dimmer Curve (Settings) from the Menu					
Channel	Function	Values			
1	Master Dimmer	000	-	255	Dimmer 0 - 100%

2-CHANNEL-MODE					
Preselect Dimmer Response and Dimmer Curve from the Menu (Settings)					
Channel	Function	Values			
1	Cold White	000	-	255	Dimmer 0 - 100%
2	Warm White	000	-	255	Dimmer 0 - 100%

3-CHANNEL-MODE 1					
Preselect Dimmer Response and Dimmer Curve from the Menu (Settings)					
Channel	Function	Values			
1	Master Dimmer	000	-	255	Dimmer 0 - 100%
2	Colour Temperature	000	-	005	off
		006	-	255	cold - warm
3	Strobe	000	-	005	Strobe open
		006	-	255	Strobe slow -> fast (1Hz - 20Hz)

3-CHANNEL-MODE 2					
Preselect Dimmer Response and Dimmer Curve from the Menu (Settings)					
Channel	Function	Values			
1	Master Dimmer	000	-	255	Dimmer 0 - 100%
2	Cold White	000	-	255	Dimmer 0 - 100%
3	Warm White	000	-	255	Dimmer 0 - 100%

7-CHANNEL-MODE					
Channel	Function	Values			
1	Master Dimmer	000	-	255	Dimmer 0 - 100%
2	Multifunctional Strobe	000	-	005	Strobe open
		006	-	010	Strobe closed
		011	-	033	Pulse Random, slow -> fast
		034	-	056	Ramp up Random, slow -> fast
		057	-	079	Ramp down Random, slow -> fast
		080	-	102	Random Strobe Effect, slow -> fast
		103	-	127	Strobe Break Effekt, 5s.....1s (Short burst with break)
		128	-	250	Strobe slow -> fast (1Hz - 20Hz)
		251	-	255	Strobe open
3	Cold White	000	-	255	Dimmer 0 - 100%
4	Warm White	000	-	255	Dimmer 0 - 100%

5	Colour Temperature	000	-	005	off
		006	-	255	cold - warm
6	Dimmer Response	000	-	005	no function
		006	-	127	Dimmer Response LED
		128	-	255	Dimmer Response Halogen
7	Dimmer Curves	000	-	005	no function
		006	-	063	Linear Dimmer Curve
		064	-	127	Exponential Dimmer Curve
		128	-	191	Logarithmic Dimmer Curve
		192	-	255	S-Curve Dimmer Curve