



SHOWTEC Showdesigner 512 jeu d'orges DMX pour automatiques et trad

CARACTERISTIQUES GENERALES :

Réf : SHOWDES512



SHOWTEC Showdesigner 512 jeu d'orges DMX pour automatiques et trad

Showdesigner 512

Moving Light Controller

- ? Control 32 fixtures up to 16 channels each
- ? 48 Scenes/Chases can run simultaneously
- ? Each chase can store 200 steps
- ? 3 patchable master faders
- ? Intelligent jogwheel

- ? Compact versatile moving light controller

- ? 512 DMX Channels

- ? 1 Photoelectric isolated outputs

- ? Easy programming

- ? Large LCD display

Power supply: AC 100-240V 50/60 Hz

Power consumption: 30 Watt

DMX Channels: 512

Fixtures: 32 with each 16 channel

Scenes: 48 can simultaneously run

Chases: 48 can simultaneously run with each 200 steps

Outputs: 2 Isolated 3 Pin XLR female

Pan/Tilt: 16 bit



Audio: External audio input and internal audio triggering

Dimensions: 483 x 290 x 95 mm (LxWxH)

Weight: 5,6 kg

PROZIC
113 Ancienne route Imperiale
31120 Portet-sur-Garonne
05 82 950 710

Packaging :

Dimensions produit :

Poids : 6Kg

Données non contractuelles